
Accessories AC Solid-core Current Transformer Type CTD-8Q (27 max 55x100 mm)

CARLO GAVAZZI



Product Description

Solid-core current trans- Rated primary current from former with bus-bar mount- 1000 to 4000A. ing facility.

Bus-bar type solid-core current transformer

- Accuracy class 0.5
- Current range from 1000 to 4000A
- Up to 8 bus-bar fixing screws
- Double screw terminals (up to 4-wire connections)
- Sealable terminal block covers



Model	5	
Primary current		
Secondary current		
Option		

-30°C to +40°C (-22°F to

104°F) (R.H. < 90% non condensing @ 40°C)

-30°C to +70°C (-22°F to 158°F) (R.H. < 90% non

Type Selection

Model	Primary current	Secondary current	Option	
CTD-8Q	1000 1500 2000 2500 3000 4000	5A	XXX: none	

Input Specifications

Operating frequency	50-60 Hz
Max. system voltage	0.72 kV
Rated insulation level	3 kV/1 min. @ 50 Hz
Insulation class	В
Short-time current rating I _{th} I _{dyn}	Typical 100 I_n /1 s 2.5 I_{th} The short-time thermal current I_{th} is anyway limited by the cable/bus-bar size
Security factor (FS)	≤ 10

In /1 s condensing @ 40°C) ime thermal Approvals CE connection Screw type cable cross section area From 1.5 to 4 mm² Protection degree IP20 Bus-bar size Max. 55x100 mm Weight < 1.1 Kg</td>

Working temperature

Storage temperature

General Specifications

Standards	According to EN60044-1
Housing	Polycarbonate UL94 V2
Mounting	Bus-bar mounting
Standard accessories	Two terminal block screws. Eight bus-bar fixing screws. Two sealable terminal block covers.

Output Specifications

Rated secondary current	5 A
Burden	15 VA

Wiring Diagram



Dimensions (mm)

